

# ECB600

Dual Band Long Range Multi-Function Access Point/Client Bridge

- 2.4 GHz + 5GHz
- 300+300Mbps
- 29dBm
- AP/CB/WDS/Repeater

## PRODUCT OVERVIEW



**ECB600** is a wireless-11n 600Mbps (300Mbps + 300Mbps) Dual Band concurrent Access Point/ Client Bridge. It allows simultaneous operation of 2.4GHz and 5GHz wireless network. With media-optimized performance, you can enjoy internet surfing more smoothly and with less lag.

MSSID + VLAN make your data more secure and easy management. Standard PoE interoperable with 802.3af/at makes internet connection more flexible.

ECB600 designed with 4 detachable high gain antennas which deliver larger coverage and higher throughput in the environment. Elegant body and white outlook will upgrade aesthetic feeling on your desk in working environment. ECB600 is the best choice in business office.

SOFTWARE FEATURES		
<b>SYSTEM REQUIREMENT</b>		
<b>System</b>	Windows7, 98, ME, NT, XP, 2000. Mac OS X (10.4)	
<b>Access method</b>	Web Based (HTTP 1.0 / 1.1)	
<b>Browser Compatibility</b>	Microsoft IE 6.0 or above, Firefox 2.0 or above	
<b>STATUS</b>		
<b>System Status</b>	System Information	System Up Time, Device Name, Wireless MAC, LAN MAC, Country, Current Time, Firmware Version
	Current IP Setting	IP Address, Subnet Mask, Default Gateway, DHCP, DNS.
	Current Wireless Setting	Operation mode, Wireless Mode, Channel/Frequency, L2 Isolation, MSSID Setting
<b>Client List</b>	List current associated clients. Show only authorized and associated clients	
<b>System Log</b>	Displays a list of events triggered	
<b>Wireless Functional List</b>		
<b>Operation mode</b>	AP	
	CB	
	WDS	
	Repeater	
<b>WDS detail</b>	WDS AP	
	WDS bridge	
	WDS station	
<b>802.11 mode options</b>	a/b/g/n	
<b>Band Steering</b>	Band steering steers 5GHz-compatible clients to 5GHz band and leave 2.4 GHz band for single band (2.4GHz) client using.	
<b>Channel setting</b>	Manual	
	Auto / Best Channel Selection	
<b>Transfer rate setting</b>	Auto and Manual	
<b>Output Power Control</b>	Select by dBm	
<b>Multiple BSSID (Multi AP)</b>	8 BSSID for 2.4Ghz , another 8BSSID for 5Ghz	

		Each BSSID should has its own WiFi & security settings	
<b>WPS</b>		Software only	
Security	WEP	WEP (64/128bit)	
	WPA/WPA2-PSK	TKIP/AES	
	MAC address filtering	MAC address filtering (WLAN, up to 50 fields)	
	Support EAP	EAP-TLS	
		EAP-TLS/MSCHAPv2	
		PEAPv0/EAP-MSCHAPv2	
		PEAPv1/EAP-GTC	
		EAP-SIM	
	802.1x Authenticator	MD5/TLS/TTLS/PEAP	
	Hidden ESSID	Supported	
MAC Address	MAC Address filtering (WLAN, up to 50 fields)		
L2 Isolation	Supported		
<b>LAN Settings</b>		IP (check vability)	
<b>VLAN</b>	MSSID	VLAN tag on MSSID	
	Management VLAN Ethernet Port VID	Only allow user with specified VID to access the device	
	Tag/Untag Option	Independent VLAN setting can be enable or disable	
	Add VLAN Tag	Any packet that enters the Device without a VLAN tag will have a VLAN tag inserted with a PVID (Ethernet Port VID)	
	VLAN Pass Through	VLAN Pass Through over WDS bridge	
<b>SNMP</b>	SNMP V1/V2C	SNMP Active : Disabled/Enabled	
	MIBI, MIBII	SNMP Version : V1/V2c/ALL	
	Private MIB	Read Community Set Community System Location System Contract Trap Active :Disabled/Enabled	

<b>QoS</b>	WMM (Default)		
	Load Balance Per SSID		
<b>Administration</b>	User Name (set as "admin", can be changed by user)		
	Password s(et as "admin", can be changed by user)		
<b>Backup/Restore Setting</b>	Save current setting		
	Restore Saved Setting		
	Reset to Factory Default		
<b>Firmware Upgrade</b>	Supported		
<b>UPnP</b>	Supported		
Advanced Management	Auto Reboot		
	CLI		
	NMS (EZ Controller) supported		
<b>HARDWARE SPECIFICATIONS</b>			
<b>MCU</b>	AR9344 + AR9382		
<b>Memory/Flash</b>	64MB/16MB		
<b>Dimension</b>	189 x 140 x 26 mm		
<b>Physical Interface</b>	LAN : 1x10/100/1000 Gigabit Ethernet (802.3at PoE standard supported)		
	Reset		
	Power Jack		
	Power on/off switch		
<b>LED Definition</b>	Power x 1	Orange	Booting : Blink at 1Hbooting System Ready : ON Firmware Upgrade : Blink at 4HZ System Off : Power Off
	LAN x1	Blue	Link : Solid Light / Active Blinking (Receiving/Transmitting Data)
	WLAN x2	2.4G Blue 5G Blue	Link : Solid Light/Active Blinking (Receiving/Transmitting data)
<b>Adapter</b>	12V/2A		

SPECIFICATIONS			
WIRELESS SPECIFICATIONS			
<b>Frequency Band</b>	Radio I: 11b/g/n : 2.412~2.484 GHz Radio II: 11a/n :5.18 ~ 5.24 & 5.26 ~ 5.32 & 5.5 ~ 5.7 & 5.745 ~ 5.825 GHz		
<b>Modulation Technology</b>	OFDM: BPSK, QPSK, 16-QAM, 64-QAM DBPSK, DQPSK, CCK		
<b>Operating Channels</b>	2.4G (11 for North America, 14 for Japan, 13 for Europe) 5G (TBD)depend on what region		
<b>Wireless Setting</b>	Operation Mode – AP / CB/ WDS / Repeater Wireless Mode – 11a/ 11b/ 11g /11n Channel Selection (Setting varies by Country) Channel Bandwidth (Auto, 20Mhz, 40Mhz) Transmission Rate – 2.4GHz: 11n only ,11b/g/n mix ,11b only ,11b/g, 11g only 5GHz: 11n only mode, 11a/n mix mode, 11a only mode		
<b>Receive Sensitivity (Typical)</b>	<b>802.11b</b> -99dBm @ 1Mbps -93dBm @ 11Mbps  <b>802.11g</b> -96dBm @ 6Mbps -82dBm @ 54Mbps  <b>802.11n (2.4GHz)</b> -97dBm @ MCS0 -78dBm @ MCS7 -96dBm @ MCS8 -76dBm @ MCS15		<b>802.11a</b> -90dBm @ 6Mbps -72dBm @ 54Mbps  <b>802.11n (5GHz)</b> -89dBm @ MCS0 -70dBm @ MCS7 -89dBm @ MCS8 -70dBm @ MCS15
<b>Available transmit power (2 stream)</b> <b>(The Max. Power may be different depending on local regulations)</b>	11b	1Mbps - 11Mbps	29
	11g	6Mbps - 9Mbps	29
		12Mbps - 18Mbps	28
		24Mbps - 36Mbps	24
		48Mbps - 54Mbps	23
	11n	MCS 0-1 / 8-9	29
		MCS 2-3 / 10-11	28
		MCS 4-5 / 12-13	24
MCS 6-7 / 14-15		23	
11a	6Mbps - 9Mbps	26	

		12Mbps - 18Mbps	25
		24Mbps - 36Mbps	24
		48Mbps - 54Mbps	23
	11n	MCS 0-1 / 8-9	26
		MCS 2-3 / 10-11	25
		MCS 4-5 / 12-13	24
		MCS 6-7 / 14-15	23
<b>Antenna</b>	External Omni Detachable Antenna (2.4GHz *2/ 5GHz *2)		

ENVIRONMENT AND MECHANICAL	
<b>Temperature Range</b>	0 to 50° C - Operating, -20 to 60 ° C - Storage
<b>Humidity (non-condensing)</b>	90% or less – Operating, 90% or less - Storage

CERTIFICATION	
<b>FCC</b>	Certified
<b>CE</b>	Certified
<b>IC</b>	Certified

PACKAGE CONTENT
▶ 1 x ECB600
▶ 1 x Power Adapter
▶ 1 x QIG
▶ 1 x CD (User's Manual)
▶ 1 x Ethernet Cable
▶ 1 x Wall Mount Kit
▶ 4 x Detachable Antennas